

IJ-25/IJ-25 Pro fitting instructions



approved
manufacturers, suppliers and
maintainers of franking machines

PLEASE ONLY LOAD THE CARD ONCE BEFORE 4th APRIL 2022, LOADING TWICE WILL DELETE YOUR PREVIOUS TARIFF.

These tariffs can be loaded now. Tariffs will automatically update only on the effective date (please see www.royalmail.com/prices2022 for details).

If you experience any problems after loading the new tariff, turn the machine OFF then ON. Call the Tariff Change Help Desk on: 0845 880 0000 or Email us: www.quadi^{ent}.com/en-GB/customer-care

1

FROM YOUR READY SCREEN

2

PRESS **MENU** AND THEN SCROLL (<>) TO MEMORY CARD

3

PRESS **OK**
THEN INSERT CARD WITH GOLD CHIP AT THE BOTTOM, FACING
DOWN TOWARDS YOU

4

PRESS **OK** TWICE
IF YOUR MACHINE SAYS "REPLACE FILE" PRESS **OK**, IF NOT,
CONTINUE TO STEP 5

5

AFTER A SHORT PERIOD MACHINE WILL SAY
"MEMORY CARD LOADING COMPLETE"

6

TO RETURN TO READY MODE TURN THE MACHINE OFF AT THE POWER
SUPPLY, WAIT FOR 5 SECONDS THEN RESTART THE MACHINE. THE
CARD CAN NOW BE REMOVED